

Tach Products

Powered Mixers

TA-120CD/TA-200CD

120W / 200W Powered Mixer with CD Player



Features:

- ⊙ Quality sound output as good as that of Hi-Fi stereo systems
- ⊙ emergency alarm priority function
- ⊙ CD player with Japanese parts and remote control
- ⊙ USB input for audio input from MP3 player
- ⊙ Modular CD player allows easy installation & maintenance from front panel

Specifications:

- Power output : 120W RMS / 200W RMS
- Power Supply : AC 230V 60Hz, DC 24V
- Loaded impedance : 100V.70V.0V, 16Ω.8Ω.4Ω.0Ω.
- Input : MIC × 3, LINE × 3(LINE 1 and LINE2 can be switched to MIC)
- Frequency response : 20Hz ~ 15KHz ± 3dB
- Distortion rate : 0.1% ±5 (1KHz Output)
- Tone control : Bass ± 10dB, Treble ± 10dB
- REC OUT : 1KΩ 0dB
- CD player : Parts from Japan, DC 12V
- Color: Black
- Dimension:420mm(W) × 102mm(H) × 335mm(D)
- Weight:10.9KG/12.1KG